60×60×15 mm

San Ace 60WF 9WF_{type} 🚱 🔎 🔊



General Specifications

· Material	Frame: Plastic (Flammability: UL 94V-0), Impeller: Plastic (Flammability: UL 94V-0)
· Expected life	See the table below. (L10 life: 90% survival rate for continuous operation in free air at 60 °C, rated voltage) Expected life at 40 °C is for reference only.
· Motor protection function	Locked rotor burnout protection, Reverse polarity protection For details, please refer to p. 614.
· Dielectric strength	50/60 Hz, 500 VAC, for 1 minute (between lead wire conductors and frame)
· Insulation resistance	10 $\mbox{M}\mbox{\Omega}$ min. at 500 VDC (between lead wire conductors and frame)
· Sound pressure level (SPL)	A-weighted sound pressure level (SPL) at 1 m away from the air inlet.
· Storage temperature	-30 to +70°C (Non-condensing)
· Lead wire	⊕Red ⊝Black Sensor Yellow

This fan can be used in environments with oil mist.*

Specifications —

The models listed below have ribs and a pulse sensor.


Model no.	Rated voltage	Operating voltage range	Rated current	Rated input	Rated speed	Max. airflow		Max. static pressure		SPL	Operating temperature	Expected life
	[V]	[V]	[A]	[W]	[min-1]	[m³/min]	[CFM]	[Pa]	[inchH ₂ 0]	[dB (A)]	[°C]	[h]
9WF0624H701	24	20.4 to 27.6	0.12	2.88	6800	0.52	18.3	95	0.38	44	-20 to +70	40000/60°C (70000/40°C)

Note: Sensor and control options are available for selection. Refer to the table on p. 654.


Airflow - Static Pressure Characteristics


9WF0624H701 With pulse sensor

Operating voltage range




^{*} Environment where cutting oil creates oil mist. Conduct a product evaluation with the type of oil to be used.





Reference Dimensions of Mounting Holes and Vent Opening (unit: mm)

Inlet side, Outlet side



Options

Finger guards

page: p. 598

Model no.: 109-139E, 109-139H